

**Kemo Electronic GmbH**

Mato Vukovic  
 Leher Landstr. 20  
 27607 Geestland  
 Germany

Phone: +49 4743 9338-0  
 Fax: +49 4743 9338-22

<http://www.kemo-electronic.de>  
 email: [info@kemo-electronic.de](mailto:info@kemo-electronic.de)

HR.Nr. HRB 111 486  
 UstNr: DE 814 380 369

## M015N - DC/DC Converter, adjustable



Max. 1.5 A, Input: 6 - 28 V/DC, Output: 3 - 15 V/DC

The input voltage must be at least 3 V higher than the adjusted output voltage.  
 The adjusted output voltage is stabilized and short circuit-proof. For operation of appliances with lower voltages at a 12 V or 24 V car battery or power supplies.

### Technical Data:

Input voltage: 6 - 28 V/DC

Output voltage adjustable: 3 - 15 V/DC (electronically stabilized)

Note: The input voltage must be at least 3 V higher than the adjusted output voltage

Max. output current: 1,5 A

Max. dissipation: approx. 3 W without heat sink, approx. 10 W with heat sink (not enclosed)

Dimensions: approx. 60 x 45 x 20 mm (without fastening straps)

**M015N**

